




SUGGESTED MOUNTING FOR CO CRAFT LITE®


SURFACE & MARINE INSIDE

1. Remove end cap by loosening screws.
2. Grasp lens on one end and remove from channel.
3. Remove reflector/ballast cover by removing two (2) screws.
4. Mount luminaire utilizing four (4) mounting holes and properly seal.
5. When end wiring this luminaire, wires must pass through the electrical fitting, threaded ring and end cap, prior to making electrical connections. (Marine Inside models require wiring connections to terminal block.)
NOTE: Hubs are an option on this luminaire.
6. Replace reflector/ballast cover, install lamp(s), lens, end caps, and securing screws.




MARINE DRIP PROOF

1. Remove threaded rings and end caps. Remove threaded plug from end to be wired.
2. Grasp lens on one end and remove from channel.
3. Remove reflector/ballast cover by removing two (2) screws.
4. Mount luminaire utilizing four (4) holes in mounting brackets.
5. When end wiring this luminaire, wires must pass through the electrical fitting, threaded ring and end cap, prior to making electrical connections to terminal block.
6. Replace reflector/ballast cover, install lamp(s), lens, end caps, threaded rings and electrical fittings.
MARINE INSIDE MODELS, use Surface Mounting instructions.



PENDANT

1. Remove end caps by loosening screw.
2. Grasp lens on one end and remove from channel.
3. Remove reflector/ballast cover by turning the two (2) quarter-turn fasteners.
4. Install pendants to luminaire and properly seal.
5. Make electrical connections to supply wires brought through pendants. (End wiring; See Surface Mounting #5)
6. Replace reflector/ballast cover, install lamp(s), lens, end caps, threaded rings and electrical fittings.



Cleaning Instructions: Wipe luminaire with a soft cloth slightly dampened with warm, soapy water. On stainless steel units, tightly adhering deposits may be removed by using a stainless steel polishing powder. Never use steel wool or steel brushes on stainless steel. Always rub in the directions of the polish lines.

Note: All luminaires to be installed by a qualified electrician.
Mounting and electrical hardware not supplied by Paramount Industries unless otherwise noted.